



BE 1/2
220 - 240V
50/60Hz
18W - 58W

- Class 1 ballast for built-in use
- Start with pre-heating for longer lamp life (cut-off function)
- Input and output on opposite sides. Connector cross section 0.5 - 1.5 mm²
- Protection against mains voltage spikes and constant lamp power in case of mains voltage variations
- Intelligent electronic digital control gear and self protection levels
- Continuous checking of mains voltage input
- End of life and rectifying effect detection
- IDC connections available upon request

Ballast Reference	Power W	Lamp	Cap	ta °C	tc °C	EEL Index	λ	Weight kg	Dimensions mm			
									W	H	L ₁	L ₂
BE 136-2	1 x 18/30/36	T8	G13	-20 +50	70	A2	0.95	0.225	40	28	230	220
	1 x 18/36	TC-L	2G11	-20 +50	70	A2	0.95	0.225	40	28	230	220
	1 x 24/39	T5	G5	-20 +50	70	A2	0.95	0.225	40	28	230	220
BE 158-2	1 x 58	T8	G13	-20 +50	70	A2	0.96	0.225	40	28	230	230
	1 x 55	TC-L	2G11	-20 +50	70	A2	0.96	0.225	40	28	230	220
	1 x 54	T5	G5	-20 +50	70	A2	0.96	0.225	40	28	230	220
BE 236-2	1-2 x 18/30/36	T8	G13	-20 +50	70	A2	0.98	0.235	40	28	230	220
	1-2 x 18/36	TC-L	2G11	-20 +50	70	A2	0.98	0.235	40	28	230	220
	1-2 x 24/39	T5	G5	-20 +50	70	A2	0.98	0.235	40	28	230	220
BE 258-2	1-2 x 58	T8	G13	-20 +50	70	A2	0.98	0.235	40	28	230	220
	1-2 x 55	TC-L	2G11	-20 +50	70	A2	0.98	0.235	40	28	230	220
	1-2 x 54	T5	G5	-20 +50	70	A2	0.98	0.235	40	28	230	220

Approvals

EN-61347-2-3 EN-61000-3-2 EN-61547
EN-60929 EN-55015

